

Use VoIP Phone Service

How to config Nextiva on Ecsow Dialer

Step 1, Getting Nextiva SIP Information.

1. For administrators, log in to the NextOS Portal by going to www.nextiva.com and selecting **Customer Login** from the top right corner. Enter your login credentials and click **Sign in**. Select **Sites & Employees** then click on **Login** under the Admin Login column. Click **Users** and search for the employee whose information you wish to edit. Click **Edit**.
For users, log in to the Customer Portal by going to cp.nextiva.com.
2. Click **View & Edit Devices**, then select **Add New Device**.
3. Click on **Bring Your Own Device**.
4. From the Device Type drop down menu, select **Generic SIP Phone** then click **Continue**.
5. From here, you will need to assign the Generic SIP Phone to an employee. Click on **Sites & Employees**. Then click on **Employees**.
6. Click **Edit** next to the employee who you wish to assign the phone.
7. Click **Assign New Device** in the Assigned Devices field.
8. From the **Device** drop down menu, select **Generic SIP Phone**. Then click **Generate** next to the Authentication Password. Write down the SIP Username, the Authentication Name, and the Authentication Password (you will later enter these into the soft phone), then click **Submit**.

Step 2, Fill in the Nextiva SIP Account on Ecsow Dialer.

The screenshot shows the 'Options' dialog box with the 'SIP Account' tab selected. The 'Device Information' box on the left contains the following fields:

- Device: Generic SIP Phone
- SIP Username: 37416790000
- Domain: prod.voipdnsservers.com
- Authentication Name: yoluskarter@prod
- Authentication Password: 49613790000

The 'SIP Account' tab in the dialog box contains the following fields:

- Display Name: Call Plan A
- SIP ID / User Name: 37416790000
- Domain: prod.voipdnsservers.com
- Authorization User: yoluskarter@prod
- Password: [Redacted]
- Outbound Proxy: Send outbound calls via: Domain, Proxy
- Concurrent Calls: Number of concurrent calls: 1

Colored lines connect the fields in the 'Device Information' box to the corresponding fields in the 'SIP Account' tab: a green line connects SIP Username to SIP ID / User Name, an orange line connects Domain to Domain, a blue line connects Authentication Name to Authorization User, and a light blue line connects Authentication Password to Password.

(Notes: You may need to set Send outbound via: Select "Proxy ," and

Use VoIP Phone Service

input **prod.voipdnsservers.com:5062**)

Click OK button to apply the settings.

Unique solution ID: #1033

Author: eva

Last update: 2016-01-19 04:35